

The present invention relates, inter alia, to a driver circuit. One particular application of such a driver circuit is for driving a pixel of an organic electroluminescent device.

An organic electro-luminescent (OEL) element comprises a light emitting material layer sandwiched between an anode layer and a cathode layer. Electrically, this element operates like a diode. Optically, it emits light when forward biased and the intensity of the emission increases with the forward bias current. It is possible to construct a display panel with a matrix of OEL elements fabricated on a transparent substrate and with at least one of the electrode layers being transparent. One can also integrate the driving circuit on the same panel by using low temperature polysilicon thin film transistor (TFT) technology.

In a basic analog driving scheme for an active matrix OEL display, a minimum of two transistors are required per pixel (Figure 1): T_1 is for addressing the pixel and T_2 is for converting the data voltage signal into current which drives the OEL element at a designated brightness. The data signal is stored by the storage capacitor C_{storage} when the pixel is not addressed. Although p-channel TFTs are shown in the figures, the same principle can also be applied for a circuit with n-channel TFTs.

There are problems associated with TFT analog circuits and OEL elements do not act like perfect diodes. The light emitting material does, however, have relatively uniform characteristics. Due to the nature of the TFT fabrication technique, spatial variation of the TFT characteristics exists over the entire panel. One of the most important considerations in a TFT analog circuit is the variation of threshold voltage, ΔV_T , from device to device. The

A circuit shown in figure 2 is proposed as one of built-in for compensating a variation of transistor characteristics. In this circuit, T_1 is for addressing the pixel. T_2 operates as an analog current control to provide the driving current. T_3 connects between the drain and gate of T_2 and toggles T_2 to be either a diode or in saturation. T_4 acts as a switch. Either T_1 or T_4 can be ON at any one time. Initially, T_1 and T_3 are OFF, and T_4 is ON. When T_4 is OFF, T_1 and T_3 are ON, and a current of known value is allowed to flow into the OEL element, through T_2 . This is the programming stage because the threshold voltage of T_2 is measured with T_2 operating as a diode (with T_3 turned ON) while the programming current is allowed to flow through T_1 , through T_2 and into the OEL element. T_3 shorts the drain and gate of T_2 and turns T_2 in to a diode. The detected threshold voltage of T_2 is stored by the capacitor C_1 connected between the gate and source terminals of T_2 when T_3 and T_1 are switched OFF. Then T_4 is turned ON, the current is now provided by V_{DD} . If the slope of the output characteristics were flat, the reproduced current would be the same as the programmed current for any threshold voltage of T_2 detected. By turning ON T_4 , the drain-source voltage of T_2 is pulled up, so a flat output characteristic will keep the reproduced current the same as the programmed current. Note that ΔV_{T2} shown in figure 2 is imaginary, not real.

A constant current is provided, in theory, during the active programming stage, which is t_2 to t_5 in the timing diagram shown in figure 2. The reproduction stage starts at t_6 .

Attention is, by the present invention, drawn to the fact that all currents passing through the circuit of figure 2 pass through the OBL element. The significance of this to the present invention will be apparent from the description given hereinafter.

According to a second aspect of the present invention there is provided a driver circuit for driving a pixel of an electroluminescent device, the pixel including an electroluminescent element and the circuit comprising; a transistor connected so as operatively to control the current supplied to the electroluminescent element, a capacitor connected for storing an operating voltage of the transistor during a programming stage, a first switching means connected so as to establish when operative a current path through the transistor during the programming stage, and a second switching means connected so as to establish when operative a current path through the transistor and the electroluminescent element during a

According to a third aspect of the present invention there is provided a driver circuit for driving a pixel of an electroluminescent device, the pixel including an electroluminescent element and the circuit comprising; a transistor connected so as operatively to control the current supplied to the electroluminescent element, a capacitor connected for storing an operating voltage of the transistor during a programming stage, a first switching means connected so as to establish when operative a current path through the transistor during the programming stage, a second switching means connected so as to establish when operative a current path through the transistor and the electroluminescent element during a reproduction stage, and a current sink, the first switching means being connected such that the current path during the programming stage is through the transistor to the current sink.

According to a fourth aspect of the present invention there is provided a method of controlling the current supply to an electroluminescent element comprising the steps of providing a current path during a programming stage which path does not pass through the electroluminescent element and of providing a current path during a reproduction stage which path does pass through the electroluminescent element.

According to a fifth aspect of the present invention there is provided a method of controlling the current supply to an electroluminescent element comprising the steps of providing a current path during a programming stage which path connects to a current sink and of providing a current path during a reproduction stage which path passes through the electroluminescent element.

According to a sixth aspect of the present invention there is provided an electroluminescent display device comprising one or more driver circuits according to any of the first to third aspects of the present invention.

According to a seventh aspect of the present invention there is provided an electronic apparatus incorporating an electroluminescent display device according to the sixth aspect of the present invention.

According to an eighth aspect of the present invention there is provided a circuit comprising a current driven element, the circuit providing a first current path including the current driven element and a second current path not including the current driven element.

According to a ninth aspect of the present invention there is provided a circuit comprising a current driven element, the circuit providing a first current path flowing a current through the current driven element, and a second current path not flowing current through the current driven element.

According to a tenth aspect of the present invention there is provided a method for driving a circuit comprising a current driven element and a transistor that controls a current supplied to the current driven element, comprising a step of determining a gate voltage of the transistor based on a predetermined current.

It will be noted that according to the present invention no current is applied to the current driven element by the current controlling transistor during the programming stage. In accordance with the invention in an electroluminescent device a pixel driver circuit can be implemented without degrading the perceived image presented by the electroluminescent device. It has the benefit of reducing the overall power consumption compared with the prior art in which the same current is supplied to the OEL element during both the programming and the reproduction stage. Furthermore, the circuit can be operated from a normal supply

09699915.070901

11

•

•

voltage compensation,

invention,

invention,

figure 4,

element and pixel driver according to an embodiment of the present invention,

invention,

invention,

Figure 9 shows another embodiment of a pixel driver circuit according to the present invention,

Figure 10 is a schematic view of a mobile personal computer incorporating a display device having a pixel driver according to the present invention,

Figure 11 is a schematic view of a mobile telephone incorporating a display device having a pixel driver according to the present invention,

Figure 12 is a schematic view of a digital camera incorporating a display device having a pixel driver according to the present invention,

Figure 13 illustrates the application of the driver circuit of the present invention to a magnetic RAM,

Figure 14 illustrates the application of the driver circuit of the present invention to a magnetoresistive element,

Figure 15 illustrates the application of the driver circuit of the present invention to a capacitance sensor or a charge sensor,

Figure 16 illustrates the application of the driver circuit of the present invention to a night vision camera, and

Figure 17 is a brief outline of an alternative implementation of the circuit of figure 4.

A pixel driver circuit according to a first embodiment of the present invention is shown in figure 3. Transistor T_2 operates as an analog current control to provide the driving current to the OEL element. Also, the storage capacitor C_1 is connected between the gate and the source of transistor T_2 . In the circuit of figure 2, a current source is operatively connected to the source of transistor T_2 by transistor T_1 , during the programming stage, and current is thus applied to the OEL element. In the embodiment of the present invention, transistor T_1 operatively connects transistor T_2 to a current sink during the programming stage. That is,

1050705166660

according to the present invention, during the programming stage no current is supplied through transistor T_2 to the OEL element. In the circuit of figure 3, the drain of transistor T_2 is connected to the source of transistor T_1 via the source/drain path of transistor T_3 . The source of transistor T_1 is connected to the gate of transistor T_2 and the gates of transistors T_1 and T_3 are connected together. The programming voltage V_p is applied to the gates of T_1 and T_3 . Transistor T_4 , which is switched off during the programming stage, connects the drain of T_2 and the source of T_3 to the OEL element. During the programming stage, transistor T_1 operatively connects transistor T_2 to a current sink which is tied to ground or a reference voltage.

The circuit of figure 3 operates in the programming stage with T_4 switched off and T_1 and T_3 switched on. T_3 being switched on has the effect of making T_2 act as a diode and T_1 connects this diode to the data current sink. As a result, capacitor C_1 charges (or discharges, depending on the voltage stored during the previous frame). Capacitor C_1 charges to the gate/source voltage of transistor T_2 and thus stores the voltage (V_{GS2} , corresponding to the data current I_{DAT}) which will control the current supply to the OEL element during the reproduction stage. At the end of the programming stage, T_1 and T_3 are switched off. The voltage V_{GS2} is stored on C_1 for the remainder of the frame period. As will be readily apparent from the circuit diagram and this description, in accordance with the present invention there is no requirement for a bias voltage to provide a current source. That is, the supply voltage (V_{DD}) in figure 3 is determined by T_2 and by the OEL element and there is no requirement for a high voltage to power a current source. The maximum voltage required by the circuit is thus significantly less than that required by the circuit of figure 2.

09699915-070901

At the start of the programming stage, with T_4 switched off, it is found that the OEL element exhibits a parasitic capacitance which discharges through the device. The rate of charging of C_1 determines the time taken for the programming stage. In accordance with circuits embodying the present invention, the capacitance of C_1 can be relatively small and thus the charging can be very rapid. As a consequence, the period for which no current is applied to the OEL element by T_2 is very short compared with the whole frame. These factors, together with the persistence of vision of the human eye means that there is no perceptible degradation of a displayed image.

The off resistance of T_3 can be important, because after C_1 has been charged and T_3 is switched off, the off resistance of T_3 can affect the voltage across C_1 for the rest of the frame period. Thus, the gate/source capacitance of T_3 should preferably be small compared with C_1 .

The reproduction voltage V_R is applied to the gate of transistor T_4 . At the beginning of the reproduction stage, in the circuit of figure 3, T_4 is switched on and T_1 and T_3 remain switched off. As a result, T_2 acts as a current source with V_{GS2} biased by C_1 , thus supplying current to the OEL element. At the end of the reproduction stage T_4 is switched off, T_1 and T_3 remain switched off. This completes one cycle. The driving waveform is indicated in figure 3.

Figure 4 illustrates a second embodiment according to the present invention. The circuit of figure 4 differs from that of figure 3 in the connection of transistor T_3 . In the circuit of figure 4, T_1 is connected to C_1 through the drain/source path of T_3 . The circuit of figure 4 is preferred to that of figure 3 because T_3 is not in the current path during the programming

The forward oriented organic EL display element 131 is formed by: the pixel electrode 115 formed of Al, the opposite electrode 116 formed of ITO, the hole injection layer 132, and the organic EL layer 133. In the forward oriented organic EL display element 131, the direction of current of the organic EL display device can be set from the opposite electrode 116 formed of ITO to the pixel electrode 115 formed of Al.

The typical layout of a full display panel employing the present invention is shown schematically in figure 7. The panel comprises an active matrix OEL element 200 with analogue current program pixels, an integrated TFT scanning driver 210 with level shifter, a flexible TAB tape 220, and an external analogue driver LSI 230 with an integrated RAM/controller. Of course, this is only one example of the possible panel arrangements in which the present invention can be used.

With reference for example to the circuit of figure 3, it will be appreciated that the invention provides a data current source - in this case for the OEL element. The circuit is readily extended so as to provide an amplified and/or multiple level (current) output. The principle of such a circuit can be understood with reference to figure 8. the circuit of figure 8 comprises the circuit of figure 3 with an additional drive transistor T_5 and an additional switching transistor T_6 added. The source of T_5 is connected to V_{DD} and its gate receives the same drive voltage signal as is applied to the gate of transistor T_2 . The drain of transistor T_5 is series connected to the drain of transistor T_6 and the source of T_6 is connected to the common point of connection of transistors T_2 , T_3 and T_4 . The gate of transistor T_6 is connected to the gate of transistor T_4 . If it is assumed that the characteristic of transistor T_2 is W/L and that the characteristic of transistor T_5 is selected to be $(N-1)W/L$ then a current amplification of:-

$$I_{out} = I_{in} \times N$$

is achieved. I_{in} is the current which flows through the current sink, i.e. I_{DAT} in figures 3 and 4. I_{out} is the current which flows through the OEL element. Thus the circuit of figure 8 can be used to reduce the value of I_{DAT} compared with the circuit of figures 3 and 4, while maintaining the same current through the OEL element. Lowering the value of I_{DAT} has the advantage of enabling the operating speed of the circuit to be increased. Lowering the value of I_{DAT} also has the advantage of lowering the transmission loss experienced across a matrix of pixels, which is particularly important with respect to large scale display panels.

Of course, additional stages - each adding their own circuit of additional transistors T_5 and T_6 - can be added. With the switching transistors T_6 series connected and each receiving its own gate drive signal - as shown in figure 9 (A,B etc) - different current values can be selected to pass through the OEL element, resulting in different intensities of light output.

Preferably the circuits shown in figures 3 to 9 are implemented using thin film transistor (TFT) technology, most preferably in polysilicon.

The present invention is particularly advantageous for use in small, mobile electronic products such as mobile phones, computers, CD players, DVD players and the like - although it is not limited thereto.

Several electronic apparatuses using the above organic electroluminescent display device will now be described.

<1: Mobile Computer>

An example in which the display device according to one of the above embodiments is applied to a mobile personal computer will now be described.

Figure 10 is an isometric view illustrating the configuration of this personal computer.

<2: Portable Phone>

<3: Digital Still Camera>

Typical cameras sensitize films based on optical images from objects, whereas the digital still camera 1300 generates imaging signals from the optical image of an object by photoelectric conversion using, for example, a charge coupled device (CCD). The digital still camera 1300 is provided with an OEL element 100 at the back face of a case 1302 to perform display based on the imaging signals from the CCD. Thus, the display panel 100 functions as a finder for displaying the object. A photo acceptance unit 1304 including optical lenses and the CCD is provided at the front side (behind in the drawing) of the case 1302.

When a cameraman determines the object image displayed in the OEL element panel 100 and releases the shutter, the image signals from the CCD are transmitted and stored to memories in a circuit board 1308. In the digital still camera 1300, video signal output

terminals 1312 and input/output terminals 1314 for data communication are provided on a side of the case 1302. As shown in the drawing, a television monitor 1430 and a personal computer 1440 are connected to the video signal terminals 1312 and the input/output terminals 1314, respectively, if necessary. The imaging signals stored in the memories of the circuit board 1308 are output to the television monitor 1430 and the personal computer 1440, by a given operation.

Examples of electronic apparatuses, other than the personal computer shown in Fig. 10, the portable phone shown in Fig. 11, and the digital still camera shown in Fig. 12, include OEL element television sets, view-finder-type and monitoring-type video tape recorders, car navigation systems, pagers, electronic notebooks, portable calculators, word processors, workstations, TV telephones, point-of-sales system (POS) terminals, and devices provided with touch panels. Of course, the above OEL device can be applied to display sections of these electronic apparatuses.

The driver circuit of the present invention can be disposed not only in a pixel of a display unit but also in a driver disposed outside a display unit.

In the above, the driver circuit of the present invention has been described with reference to various display devices. The applications of the driver circuit of the present invention are much broader than just display devices and include, for example, its use with a magnetoresistive RAM, a capacitance sensor, a charge sensor, a DNA sensor, a night vision camera and many other devices.

Figure 13 illustrates the application of the driver circuit of the present invention to a magnetic RAM. In figure 13 a magnetic head is indicated by the reference MH.

0669915-070001

Figure 15 illustrates the application of the driver circuit of the present invention to a capacitance sensor or a charge sensor. In figure 15 a sense capacitor is indicated by the reference C_{sense} . The circuit of figure 15 is also applicable to other applications, such as a fingerprint sensor and a DNA sensor.

In the embodiments illustrated with reference to the above specific description the transistors have been shown as p-channel type transistors. This is not limiting of the invention. For example, figure 17 is a brief outline of an alternative implementation of the circuit of figure 4. In figure 17 n-channel transistors are used throughout the circuit, except for the drive transistor which is retained as a p-channel transistor.

It will be apparent to persons skilled in the art that other variations and modifications can be made to the arrangements described with respect to figures 3 to 16 without departing from the scope of the invention.